










расчет сечения проводника для обеспечения падения напряжения
менее 12-15%

Ток
нагрузки

удаленность потребителя от источника питания, м

А	250	300	350	400	450	500	600	700	800	1000	1250	1500
0,2												0,5
0,3										0,5	0,75	1,0
0,4								0,5	0,75	1,0	1,5	2,5
0,5							0,5	0,75	1,0	1,5	2,5	4,0
0,6					0,5	0,75	0,75	1,0	1,0	1,5	2,5	4,0
0,7				0,5	0,75	0,75	1,0	1,0	1,5	2,5	4,0	6,0
0,8			0,5	0,75	0,75	1,0	1,0	1,5	2,5	4,0	6,0	6,0
0,9		0,5	0,75	0,75	1,0	1,0	1,5	2,5	4,0	6,0	6,0	6,0
1		0,5	0,75	1,0	1,0	1,0	1,5	2,5	4,0	6,0	6,0	6,0
1,1	0,5	0,75	1,0	1,0	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0
1,2	0,5	0,75	1,0	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0	6,0
1,3	0,5	1,0	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0	6,0	6,0
1,4	0,5	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0
1,5	0,5	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0
1,6	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0
1,7	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0
1,8	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0
1,9	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0
2	1,0	1,5	2,5	4,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0	6,0

	-	0,5мм ²	
	-	0,75мм ²	Кабель ОЭК-НУ-(03нг-2А-2,7)+2х0,75)
	-	1,0мм ²	Кабель ОЭК-НУ-(03нг-4Е2-3,5)+2х1,0)
	-	1,5мм ²	
	-	2,5мм ²	Кабель ОЭК-НУ-(03нг-4Е2-3,5)+2х2,5)
	-	4,0мм ²	
	-	6,0мм ²	

составлено ООО "КабельЭлектроСвязь" для подбора комбинированного кабеля ОЭК